POWER YOUR FUTURE

Cummins Generator LG440C

KTAA19-G5

Prime Power: 440KW/550KVA

Standby Power: 484KW/605KVA



GENERATING POWER SOLUTIONS

Increased availability for new operations

Reliable, robust and versatile generator. Ready to deliver power for a next job.

Increased uptime during operations

Once installed on the end-user-site, the generator will be ready to run: "peace of mind" operation.

Reduced transport and installation costs

The compact and robust design with integrated transport features enables faster and safer transport and installation.

Reduced service & maintenance costs

Longer service intervals.

Quicker and more efficient service jobs.

Premium resale value

Designed and built to last.



- Operate safely in accordance with proper operation manual.
- To prevent trouble and accidents perform daily and preventive maintenance checks without fail.

Cummins Series 25KVA--2000KVA



FUAN LONGKAI POWER CO.,LTD.

Headquarters:

Add: Wei 5 Road, Tiehu Industrial Zone, Fuan, Fujian, China

Tel:+86-0593-6309773 Fax:+86-0593-6586988

E-mail: sales@longkaipower.com Web: www.longkaipower.com



Technical Data

Model		LG440C
Rated prime power	kva	550
Rated standard power	kva	605
Rated voltage line to line	V	400/230
Rated current	Α	794
Maximun sound level	dB(@7m)	≤100

Engine-DCEC Cummins		
Model		KTAA19-G5
Aspiration	Turb	o, Air/Air cooling
Fuel system		PT type
No. cylinders		6 in line
Displacement	Liquid	19
Bore*Stroke	mm	159*159
Compression ratio		13.9: 1
Rated speed	r/min	1500
Rated net power(with fan)	Kw	470
Governor type		EFC Electrical
Start Motor	V	24

Exhause System		
Exhause gas flow	L/s	1997
Exhause gas temp	${\mathbb C}$	429
Max back pressure	kPa	10

Aspiration System		
Max inlet pressure	kPa	6.23
Combustion volume	L/s	750
Air flow	L/s	722

Fuel System		
100% load(Prime power)	Kg/h	96
75% load(Prime power)	Kg/h	73
50% load(Prime power)	Kg/h	48
Fuel tank capacity	L	950

Lubrication System		
Oil capacity	L	50
Oil consumption	g/kwh	0.85
Oil pressure	kPa	345-483
(continuous operation)		

Cooling System		
Coolant capacity	L	26.5
Thermostat operation range	$^{\circ}\mathbb{C}$	82-93
Max water temperature	$^{\circ}\!\mathbb{C}$	104

Alternator		
Model	LONGKAI	LK544D
	STAMFORD	HCI544D-S5L1D-D4/S5L1S-D4
Phase		3
Voltage	V	400/230
Wiring Type	3 Ph	ase 4 wire, Y type
Bearing		1
Power factor		0.8
Frequency	Hz	50
Prime power	KW	440
Exciter Type	Brushle	ess, self-excitation
Voltage regulation	%	±0.5
Protection Grade		IP 23
Insulation grade		H/H

LG440C

≤1000

Controller-DEEPSEA

Model DSE6120MK3

m

Protective functions:

Low oil pressure

Altitude

- High water temperature
- High/low voltage
- High Engine Temperature and Overspeed.
- Voltage regulator frequency regulator
- Emergency stop
- Start failure



Control Module Options





- Auto generator control module
- ■Control module with" Three Remote Control" functions
- ATS auto load transfer screen
- ■Synchronising control modules
- ■Power output cabinet



Standard Features Engine(CCEC Cummins) Radiator 50°C max,fans are driven by bel 24V charge alternator Alternator: single bearing alternator IP23, insulation class H/H Standard auto control system One set of air filter, fuel filter, oil filter

Main line circuit breaker/MCCB	
Base fuel tank	•
Two 24V batteries, rac and cable	•
Exhaust system(Ripple flex exhaust pipe,	
exhaust siphon, flange, muffler	•
User manual	•

Options Battery charge \bigcirc Engine heater \bigcirc Alternator heater \bigcirc **PMG** \bigcirc Water oil separator \bigcirc Daily fuel tank \bigcirc \bigcirc Remote control panel Automatic transfer switch/ATS \bigcirc Switch box Standard: • Options:0

Warranty*


Cummins Engine


12 months from date of purchase and 1000 hours.

Generator

12 months from date of purchase or 1000 hours (whichever occurs first).

Unit Dimensions(Basic unit)







More information, pls refer to our web-site: www.longkaipower.com

Manufacturer reserves the right to make changes in model, technical specification, color, equipment and accessories without notice.